

Instruction Manual for CONFIG

HDMI Modulator single DUB-T

CONFIG FILE DOWNLOAD TO USB STICK

► Step 1

Insert the USB-stick to the USB port on the HDMI MODULATOR and press the MENU /OK button.

► Step 2

Press button ◀ twice (2 times), until

**save to usb
press key up**

appears on screen.



► Step 3

Press button ▲ and

**save to usb
success!**

appears on screen



► Step 4

Screen returns to initial display mode and the «config» file is saved to the USB-stick plugged in the USB port of the HDMI MODULATOR

CONFIG EDIT

► Step 1

Insert the USB-stick with the CONFIG file for editing to a USB port of a PC

► Step 2

Open the **jedi_config.txt** file with Windows Wordpad program

► Step 3

Any data between characters > <

(eg <Name>**TV-1**<\Name>) can be edited and configured, according to the installation requirements. Select 'save' after each change

<constellation>2<\constellation>

<channel>43<\channel>

<FEC>4<\FEC>

<FFT>1<\FFT>

<GI>0<\GI>

<Name>TV-1<\Name>

<RF_Level>0<\RF_Level>

<LCN>1<\LCN>

<audio_bitrate>6<\audio_bitrate>

<audio_farmat>0<\audio_farmat>

<videopid>1002<\videopid>

<audiopid>1001<\audiopid>

<pmtpid>1003<\pmtpid>

<serviceID>1000<\serviceID>

<video_bitrate>18<\video_bitrate>

<Netname>EDISION<\Netname>

**Output channel
adjustment**

**Channel
Name editing**
(up to 12 characters)

**When there is more
than one [1] HDMI
MODULATOR in line,
the parameters
should be configured
according to this
chart ***

*** Important:** All values in these fields should be different and in NO way the same. Example: 1001, 1002, 1003 etc, NOT: 1001, 1001, 1002, 1002 etc. In case there are more HDMI MODULATORS in the same installation, each one must have different programmed values. Example: Modulator No1: 1001, 1002...1005 etc, Modulator No2: 1006, 1007...1009 etc.

CONFIG FILE UPLOAD TO MODULATOR

► Step 1

Remove plug from mains power supply

► Step 2

Connect the USB stick to the HDMI MODULATOR's USB port
and re-connect the mains power supply

► Step 3

Display shows

**cfg from usb
Yes (*) No ()**

Press button MENU/OK and

**cfg from usb
Loading...**

appears on screen



► Step 4

HDMI MODULATOR re-boot starts, with the new config file, as set by the user